



Home > Produkte > Musikinstrumente > Pianos > P-Serie > P-225

# P-225 Neu

Übersicht **Technische Daten** Accessories Apps Downloads

		P-225	P-223	P-145	P-143
<b>Size/Weight</b>					
<b>Dimensions</b>	<b>Width</b>	1,326 mm [52-3/16"]	1,326 mm [52-3/16"]	1,326 mm [52-3/16"]	1,326 mm [52-3/16"]
	<b>Height</b>	129 mm [5-1/16"] (with music rest: 327 mm [12-7/8"])	129 mm [5-1/16"] (with music rest: 327 mm [12-7/8"])	129 mm [5-1/16"] (with music rest: 307 mm [12-1/16"])	129 mm [5-1/16"] (with music rest: 307 mm [12-1/16"])
	<b>Depth</b>	272 mm [10-11/16"] (with music rest: 362 mm [14-1/4"])	272 mm [10-11/16"] (with music rest: 362 mm [14-1/4"])	268 mm [10-9/16"] (with music rest: 320 mm [12-5/8"])	268 mm [10-9/16"] (with music rest: 320 mm [12-5/8"])
<b>Gewicht</b>	<b>Gewicht</b>	11.5 kg [25 lb, 6 oz]	11.5 kg [25 lb, 6 oz]	11.1 kg [24 lb, 8 oz]	11.1 kg [24 lb, 8 oz]
<b>Dimensions (with optional stand)</b>	<b>Width</b>	1,326 mm [52-3/16"]	1,326 mm [52-3/16"]	1,326 mm [52-3/16"]	1,326 mm [52-3/16"]
	<b>Height</b>	744 mm [29-5/16"] (with music rest: 942 mm [37-1/16"])	744 mm [29-5/16"] (with music rest: 942 mm [37-1/16"])	744 mm [29-5/16"] (with music rest: 922 mm [36-5/16"])	744 mm [29-5/16"] (with music rest: 922 mm [36-5/16"])
	<b>Depth</b>	318 mm [12-1/2"] (with music rest: 362 mm [14-1/4"])	318 mm [12-1/2"] (with music rest: 362 mm [14-1/4"])	318 mm [12-1/2"] (with music rest: 320 mm [12-5/8"])	318 mm [12-1/2"] (with music rest: 320 mm [12-5/8"])
<b>Dimensions of Packing Box</b>	<b>W x H x D</b>	1,424 mm x 362 mm x 233 mm [56-1/16" x 14-1/4" x 9-3/16"]	1,424 mm x 362 mm x 233 mm [56-1/16" x 14-1/4" x 9-3/16"]	1,424 mm x 362 mm x 223 mm [56-1/16" x 14-1/4" x 8-3/4"]	1,424 mm x 362 mm x 223 mm [56-1/16" x 14-1/4" x 8-3/4"]
<b>Control Interface</b>					
<b>Keyboard</b>	<b>Number of Keys</b>	88	88	88	88
	<b>Typ</b>	GHC keyboard with matte black keytops	GHC keyboard with matte black keytops	GHC keyboard with matte black keytops	GHC keyboard with matte black keytops
	<b>Touch Sensitivity</b>	Hard/Medium/Soft/Fixed	Hard/Medium/Soft/Fixed	Hard/Medium/Soft/Fixed	Hard/Medium/Soft/Fixed
<b>Panel</b>	<b>Language</b>	English	English	English	English
<b>Voices</b>					
<b>Tone Generation</b>	<b>Piano Sound</b>	Yamaha CFX	Yamaha CFX	Yamaha CFIIIS	Yamaha CFIIIS
	<b>Key-off Samples</b>	Yes	Yes	-	-
	<b>Virtual Resonance Modeling (VRM)</b>	Yes (VRM Lite)	Yes (VRM Lite)	-	-
	<b>Damper Resonance</b>	-	-	Yes	Yes
<b>Polyphony</b>	<b>Number of Polyphony (Max.)</b>	192	192	64	64
<b>Preset</b>	<b>Number of Voices</b>	24	24	10	10
<b>Effects</b>					
<b>Types</b>	<b>Reverb</b>	4 types	4 types	4 types	4 types
	<b>Wall EQ</b>	Yes	Yes	-	-
	<b>Intelligent Acoustic Control (IAC)</b>	Yes	Yes	-	-
	<b>Stereophonic Optimizer</b>	Yes	Yes	-	-
	<b>Sound Boost</b>	2 types	2 types	1 type	1 type
<b>Functions</b>	<b>Dual/Layers</b>	Yes	Yes	Yes	Yes
	<b>Split</b>	Yes	Yes	-	-
	<b>Duo</b>	Yes	Yes	Yes	Yes
<b>Songs</b>					
<b>Preset</b>	<b>Number of Preset Songs</b>	21 Voice Demo Songs + 50 Classics	21 Voice Demo Songs + 50 Classics	10 Voice Demo Songs + 10 Piano Preset Songs	10 Voice Demo Songs + 10 Piano Preset Songs
<b>Recording</b>	<b>Number of Songs</b>	1	1	-	-
	<b>Number of Tracks</b>	2	2	-	-
	<b>Data Capacity</b>	Approx. 100 KB/Song (approx. 11,000 notes)	Approx. 100 KB/Song (approx. 11,000 notes)	-	-
<b>Functions</b>					
<b>Overall Controls</b>	<b>Metronome</b>	Yes	Yes	Yes	Yes
	<b>Tempo Range</b>	5 - 280	5 - 280	32 - 280	32 - 280
	<b>Transpose</b>	-6 - 0 - +6	-6 - 0 - +6	-6 - 0 - +6	-6 - 0 - +6
	<b>Tuning</b>	414.8 - 440.0 - 466.8 Hz (approx. 0.2 Hz increments)	414.8 - 440.0 - 466.8 Hz (approx. 0.2 Hz increments)	414.8 - 440.0 - 466.8 Hz (approx. 0.2 Hz increments)	414.8 - 440.0 - 466.8 Hz (approx. 0.2 Hz increments)
	<b>USB Audio Interface</b>	44.1 kHz, 24 bit, stereo	44.1 kHz, 24 bit, stereo	44.1 kHz, 16 bit, stereo	44.1 kHz, 16 bit, stereo
<b>Rhythm</b>	<b>Number of Rhythms</b>	20	20	-	-
<b>Bluetooth</b>		Audio (Varies by country)	Audio (Varies by country)	-	-
<b>Storage and Connectivity</b>					
<b>Anschlüsse</b>	<b>Headphones</b>	Standard stereo phone jack (x 2)	Standard stereo phone jack (x 2)	Standard stereo phone jack (x 1)	Standard stereo phone jack (x 1)
	<b>AUX OUT</b>	[L/L+R] [R]	[L/L+R] [R]	-	-
	<b>USB TO HOST</b>	Yes	Yes	Yes	Yes
	<b>DC IN</b>	12 V	12 V	12 V	12 V
	<b>Sustain Pedal</b>	Yes	Yes	Yes	Yes
	<b>Pedal Unit</b>	Yes	Yes	Yes	-
<b>Amplifiers and Speakers</b>					
<b>Amplifiers</b>		7 W x 2	7 W x 2	7 W x 2	7 W x 2
<b>Lautsprecher</b>		(Oval (12 cm x 8 cm) + 5 cm) x 2	(Oval (12 cm x 8 cm) + 5 cm) x 2	Oval (12 cm x 8 cm) x 2	Oval (12 cm x 8 cm) x 2
<b>Power Supply</b>					
<b>AC Adaptor</b>		PA-150B or an equivalent recommended by Yamaha (Output: DC 12 V, 1.5 A)	PA-150B or an equivalent recommended by Yamaha (Output: DC 12 V, 1.5 A)	PA-150B or an equivalent recommended by Yamaha (Output: DC 12 V, 1.5 A)	PA-150B or an equivalent recommended by Yamaha (Output: DC 12 V, 1.5 A)
<b>Netzteil</b>					
<b>Leistungsaufnahme</b>		9 W (When using PA-150B AC adaptor)	9 W (When using PA-150B AC adaptor)	6 W (When using PA-150B adaptor)	6 W (When using PA-150B adaptor)
<b>Accessories</b>					
<b>Included Accessories</b>		Owner's Manual, Online Member Product Registration, Music rest, Footswitch, AC adaptor* (PA-150B or an equivalent recommended by Yamaha) *Varies by area	Owner's Manual, Online Member Product Registration, Music rest, Footswitch, AC adaptor* (PA-150B or an equivalent recommended by Yamaha) *Varies by area	Owner's Manual, Online Member Product Registration, Music rest, Footswitch, AC adaptor* (PA-150B or an equivalent recommended by Yamaha) *Varies by area	Owner's Manual, Online Member Product Registration, Music rest, Footswitch, AC adaptor* (PA-150B or an equivalent recommended by Yamaha) *Varies by area
<b>Separately Sold Accessories</b>		Headphones (HPH-150, HPH-100, HPH-50), Keyboard stand (L-200), Pedal unit (LP-1), Foot pedal (FC3A), Footswitch (FC4A, FC5), Keyboard bag (SC-KB851), AC adaptor* (PA-150B or an equivalent recommended by Yamaha), Wireless MIDI adaptor (UD-BT01) *Varies by area	Headphones (HPH-150, HPH-100, HPH-50), Keyboard stand (L-100), Pedal unit (LP-5A), Foot pedal (FC3A), Footswitch (FC4A, FC5), Keyboard bag (SC-KB851), AC adaptor* (PA-150B or an equivalent recommended by Yamaha), Wireless MIDI adaptor (UD-BT01) *Varies by area	Headphones (HPH-150, HPH-100, HPH-50), Keyboard stand (L-100), Pedal unit (LP-5A), Foot pedal (FC3A), Footswitch (FC4A, FC5), Keyboard bag (SC-KB851), AC adaptor* (PA-150B or an equivalent recommended by Yamaha), Wireless MIDI adaptor (UD-BT01) *Varies by area	Headphones (HPH-150, HPH-100, HPH-50), Keyboard stand (L-100), Foot pedal (FC3A), Footswitch (FC4A, FC5), Keyboard bag (SC-KB851), AC adaptor* (PA-150B or an equivalent recommended by Yamaha), Wireless MIDI adaptor (UD-BT01) *Varies by area

Home > Produkte > Musikinstrumente > Pianos > P-Serie > P-225



### Produkte

Klaviere, Flügel und Digital Pianos  
Keyboards und Synthesizer  
Gitarren, Bässe & Verstärker  
Drums  
Blech- und Holzblasinstrumente  
Streichinstrumente  
Konzertperkussion  
Marching-Instrumente  
Synthesizer & Musikproduktions-Tools  
Elektronische Unterhaltungsinstrumente  
Audio & Video  
Professional Audio  
Kopfhörer  
Apps  
Unified Communications

### Music Education

Yamaha Music Schools  
Music Schools finden  
Yamaha Music Foundation of Europe  
Yamaha, Ihr Partner für die musikalische Bildung

### News & Events

News & Events Startseite

### Artists

Artists Startseite

### Support

Kontakt  
Garantie-Information  
Broschüren und Kataloge  
Bedienungsanleitungen  
Firmware / Software Aktualisierungen  
Support Dokumente  
Sicherheitshinweise  
FAQ

### Social Media

Facebook  
Instagram  
Youtube  
Twitter  
LinkedIn

### Über Yamaha

Unternehmensprofil  
Unternehmens-Video  
Karriere  
Firmenphilosophie  
Promises to Stakeholders  
Firmengeschichte  
Investor Relations  
CSR (Soziales Engagement)

### Finden

Händler finden  
Service Station finden  
Music School finden

### Registrierung von „Yamaha Music ID“

Abonnieren Sie Newsletter  
Produktregistrierung  
Häufig gestellte Fragen zur Mitgliedschaft