

# SPEZIFIKATIONEN

MODEL NAME		PSR-SX920	PSR-SX720
<b>SIZE/WEIGHT</b>			
Dimensions (W x D x H)		1,017 mm x 431 mm x 139 mm (40-1/16" x 17" x 5-1/2")	
Weight		11.6 kg (25 lb, 9 oz)	
<b>CONTROL INTERFACE</b>			
Keyboard	Number of keys	61	
	Type	Organ (FSB), Initial Touch	
	Touch Response	Normal, Soft1, Soft2, Hard1, Hard2	
Other Controllers	Joystick	Yes (Assignable)	
	Knobs	2 (Assignable)	
	Assignable buttons	8 (A-F, 1-2)	
Main Display	Type	TFT Color Wide VGA LCD	
	Size	800 x 480 dots, 7 inch	
	Touch Screen	Yes	
	Language	English, Chinese, German, French, Spanish, Italian	
Panel	Language	English, Chinese	
<b>VOICES</b>			
Tone Generator		AWM Stereo Sampling	
Polyphony (max.)		128	
Preset	Number of Voices	1,587 Voices + 63 Drum/SFX Kits + 480 XG Voices	1,377 Voices + 56 Drum/SFX Kits + 480 XG Voices
	Featured Voices	12 S.Articulation2, 15 S.Articulation+, 340 S.Articulation, 55 OrganFlutes, 82 MegaVoice	9 S.Articulation+, 252 S.Articulation, 55 OrganFlutes, 54 MegaVoice
Compatibility		XG, GM, GM2 (for Song playback)	
Keyboard Parts		Right 1, Right 2, Right 3, Left	
<b>EFFECTS</b>			
Types	Reverb	59 Presets + 30 User	
	Chorus	107 Presets + 30 User	106 Presets + 30 User
	DSP	358 Presets (with VCM) + 30 User	358 Presets + 30 User
	Master Compressor	5 Presets + 30 User	
	Master EQ	5 Presets + 30 User	
	Part EQ	28 Parts	
	Vocal Harmony	54 Presets + 60 User* <small>* The number is the total of Vocal Harmony and Synth Vocoder</small>	-
	Synth Vocoder	20 Presets + 60 User* <small>* The number is the total of Vocal Harmony and Synth Vocoder</small>	-
	Others	Mic/Guitar Effects: Noise Gate, Compressor, 3 Band EQ, Vocal Effect: 23	Mic/Guitar effects: Noise Gate, Compressor, 3 Band EQ
<b>STYLES</b>			
Preset	Number of Styles	575	450
	Featured Styles	520 Pro Styles, 49 Session Styles, 6 Free Play Styles	410 Pro Styles, 37 Session Styles, 3 Free Play Styles
	Fingering	Single Finger, Fingered, Fingered On Bass, Multi Finger, AI Fingered, Full Keyboard, AI Full Keyboard, Smart Chord	
	Style Control	INTRO x 3, MAIN VARIATION x 4, FILL x 4, BREAK, ENDING x 3	
Other Features	One Touch Setting (OTS)	4 for each Style	
	Chord Looper	Yes	
	Style Section Reset	Yes	
Compatibility		Style File Format (SFF), Style File Format GE (SFF GE)	
<b>EXPANDABILITY (EXPANSION PACKS)</b>			
Expansion Voice		Yes (approx. 2 GB)	Yes (approx. 1 GB)
Expansion Style		Yes (Internal Memory)	
Expansion Audio Style		Yes (Internal Memory)	-

# SPEZIFIKATIONEN

MODEL NAME		PSR-SX920	PSR-SX720
<b>SONGS (MIDI)</b>			
Preset	Number of Preset Songs	1 Demo Song, 2 Preset Songs	
Recording	Number of tracks	16	
	Data capacity	Approx. 3 MB/Song	
	Function	Quick Recording, Multi Recording, Step Recording	
Format	Playback	SMF (Format 0 & 1), XF	
	Recording	SMF (Format 0)	
<b>SONGS (AUDIO)</b>			
Recording	Data Capacity	approx. 0.8 GB (80 minutes) per Song	
Format	Playback	WAV (44.1 kHz, 16 bit, stereo), MP3 (44.1/48.0 kHz, 64-320 kbps and VBR mono/stereo)	
	Recording	WAV (44.1 kHz, 16 bit, stereo), MP3 (44.1 kHz, 128/256/320 kbps, stereo)	
Time Stretch		Yes	
Pitch Shift		Yes	
Vocal Cancel		Yes	
<b>MULTI PADS</b>			
Number of Multi Pad Banks		500	349
Audio Link		Yes	
<b>FUNCTIONS</b>			
Voices	Harmony/Echo	Yes	
	Arpeggio	Yes	
	Panel Sustain	Yes	
	Mono/Poly	Yes	
Styles	Style Creator	Yes	
	OTS Information	Yes	
Songs	Score Display function	Yes	
	Lyrics Display function	Yes	
	Lesson/Guide	Follow Lights, Any Key, Karao-Key, Your Tempo	
Multi Pads	Multi Pad Creator	Yes	
Registration Memory	Number of buttons	8	
	Control	Registration Sequence, Freeze	
Playlist	Number of Records	2,500 (max.) Records per Playlist file	
Search		Yes	
Demo		Yes	
Overall Controls	Metronome	Yes	
	Tempo Range	5 - 500, Tap Tempo	
	Transpose	-12 - 0 - +12	
	Tuning	414.8 - 440 - 466.8 Hz	
	Octave button	Yes	
	Scale Type	9 types	
Miscellaneous	Direct Access	Yes	
	Text/Image Display function	Yes	
	Wallpaper Customization	Yes	
Others	Display output to an external monitor	Yes (by using a commercially USB display adaptor) <small>* For a list of compatible devices, access the Yamaha website (see "PSR-SX920/SX720 related downloads," page 8).</small>	-

# SPEZIFIKATIONEN

MODEL NAME		PSR-SX920	PSR-SX720	
<b>STORAGE AND CONNECTIVITY</b>				
Storage	Internal memory (USER Drive)	Yes (approx. 4 GB)	Yes (approx. 1 GB)	
	External drives	USB flash drive		
Connectivity	Headphones	Standard stereo phone jack		
	Microphone	Yes (Microphone/Guitar)		
	MIDI	IN, OUT		
	AUX IN	Stereo mini jack		
	LINE OUT	MAIN OUTPUT (L/L+R, R), SUB (AUX) OUTPUT (1,2 (L/L+R, R))	MAIN OUTPUT (L/L+R, R)	
	FOOT PEDAL	1 (SUSTAIN), 2 (ARTICULATION 1), Function assignable		
	USB TO DEVICE	Yes (x 2)	Yes	
	USB TO HOST	Yes		
	Bluetooth®	Yes (*) <ul style="list-style-type: none"> <li>• Bluetooth® version: 5.0</li> <li>• Supported profile: A2DP</li> <li>• Compatible codec: SBC</li> <li>• Wireless output: Bluetooth® class 2</li> <li>• Maximum communication distance: about 10 m</li> <li>• Radio Frequency (Operational Frequency): 2402-2480 MHz</li> <li>• Maximum output power (EIRP): +6.94 dBm</li> <li>• Type of modulation: GFSK, π/4 DQPSK, 8DPSK</li> </ul> <small>* May not be included, depending on your area. Check with your Yamaha dealer.</small>		-
<b>SOUND SYSTEM</b>				
Amplifiers		(15 W+10 W) x 2	15 W x 2	
Speakers		[13 cm FSP + 2.5 cm, (Dome type)] x 2	[13 cm + 5 cm] x 2	
<b>POWER SUPPLY</b>				
AC Adaptor		PA-300C (Output: DC 16V, 2.4 A)	PA-300C (Output: DC 16V, 2.4 A)	
Power Consumption		24 W	21 W	
Auto Power Off		Yes		
<b>ACCESSORIES</b>				
Included Accessories		Owner's Manual, Music Rest, AC Adaptor (PA-300C)		
Separately Sold Accessories (May not be available depending on your area.)		AC adaptor: PA-300C or an equivalent recommended by Yamaha Headphones: HPH-50, HPH-100, HPH-150 Footswitch: FC4A, FC5 Foot controller: FC7 USB wireless LAN adaptor: UD-WL01 Wireless MIDI adaptor: UD-BT01, MD-BT01 Subwoofer: KS-SW100 Keyboard stand: L-7B Keyboard bag: SC-KB650		